
ELECTRONIC CENTRIFUGAL SWITCHES
FOR CAPACITOR START (& RUN) INDUCTION MOTORS

ECS 125T



MODEL CHART

Switching part	Motor ratings		
	Hp	Aux. coil rating volt	Pole
BTB24-600BW	0.5~3.0Hp	100 ~ 120 VAC	2,4,6

* These models are designed for both capacitor start motors and two (start + run) capacitors motors. For motor operating voltage of 220VAC, Please refer to typical wiring diagram of this datasheet.

ELECTRICAL CHARACTERISTICS (TYPICAL RATINGS OTHER THAN SPECIFIED)



Parameter		ECS125T	Unit
Non repetitive peak current @ half cycle, 50/60Hz		250	A
Thermal impedance @ 7.4sec, 25A		0.9	°C/W
Switch-on delay time @ 50/60Hz		2	cycle
*Discharge resistor		5.0	KΩ
**Forced switch-off locked rotor time	60Hz	7.4	sec
	50Hz	8.8	sec
**Maximum Number of successive restarts		9	-
Forced switch-off starting coil voltage		200 ~ 250	V
Line voltage, VL		100 ~ 120	V
Dielectric strength, between case and pins		>2500	VDC
Insulation resistance, between case and pins		>10	MΩ
Ambient air temperature		-20 ~ 60	°C

* For frequent(hight duty)restarts, it is recommended to connect an additional resistor in parallel with starting capacitor.
**These can be initialized by either power interruptions or successful motor run states.

CERTIFICATION

IEC/ EN 60730-1(Automatic electrical controls for household and similar use)
IEC/ EN 60730-2-10(particular requirements for motor-starting relays)

TYPICAL WIRING

100~120VAC 50/60Hz Motor Operation	200~240VAC 50/60Hz Motor Operation
	

CS : Starting Capacitor, CR : Run Capacitor , M1,M2 : Main Coil , ST : Starting Coil